ENM Institute of Technology

SET-

_{06CS52}11

UST

Fifth Semester B.E. Degree Examination, Dec.08/Jan.09 System Software

Time: 3 hrs.

Max. Marks:100

Note: Answer any FIVE full questions, selecting at least TWO questions from each part.

PART - A

- 1 a. Bring out the differences between Application software and System software. (04 Marks)
 - Explain SIC/XE machine instruction formats and all addressing modes by clearly indicating the setting of different flag bits. (10 Marks)
 - Write a subroutine in SIC/XE to read a 100-byte record from a device 'F5' into BUFFER.
 Use immediate and register-to-register instructions. (06 Marks)
- Write and explain the algorithm of PASS-1 of two-pass assembler. (10 Marks)
 - b. Generate the complete object program for the following assembly level program.

	SUM	START	0
	FIRST	CLEAR	X
		LDA	#0
		+LDB	#TOTAL
		BASE	TOTAL
VT'	LOOP	ADD	TABLE, X
	. EP	TIX	COUNT
	ALL	JLT	LOOP
	OL.	STA	TOTAL
	COUNT	RESW	1
	TABLE	RESW	2000
	TOTAL	RESW	1
		END	FIRST
Test of the second		Carried Control of the Control of th	49000 A

Assume below opcodes (all in hexadecimal)

CLEAR – B4	LDA - 00	LDB - 68	ADD – 18	
TIX - 2C	II T _ 38	STA = OC		

TIX - 2C JLT - 38 STA - OC (10 Marks)

- 3 a. Distinguish between literal and immediate operands. How does the assembler handle the literal operand? (04 Marks)
 - b. Compare a two-pass assembler with a one-pass assembler. How forward references are handled in one-pass assemblers? (10 Marks)
 - c. Write a note on MASM assembler. (06 Marks)
- 4 a. Give and explain the algorithm or source program for a simple Bootstrap loader. (08 Marks)
 - Distinguish between linking loader and linkage editors. (04 Marks)
 - c. Explain dynamic linking with suitable diagrams. (08 Marks)

PART-B

- 5 a. Explain the structure of a text editor with a neat diagram. (10 Marks)
 - Explain the functions and capabilities of an interactive debugging system.
- (06 Marks)
- c. Write a note on the aspect of user-interface criteria. (04 Marks)
- a. What are the basic functions of macroprocessor? Explain the various data structures used in the implementation of a one-pass macroprocessor. (10 Marks)

```
b. Using the following definition, expand the following macro calls, called in sequence.
   (i) LABEL RDBUFF F2, BUFFER, LENGTH, (04, 12)
              RDBUFF OE, BUFF, RLENG, , 2048
   (ii)
      RDBUFF MACRO &INDEV, &BUFADR, &RECLTH, &EOR, &MAXLTH
                                 %NITEMS (&EOR)
      &EORCT
                  SET
                                 X
                  CLAER
                  CLEAR
                                 A
                  IF
                                 (&MAXLTH EQ '
                  +LDT
                                 #4096
                  ELSE
                                 #&MAXLTH
                  +LDT
                  ENDIF
                                 =X '&INDEV'
                  TD
      $LOOP
                                 $LOOP
                  JEO
                                 =X '&INDE
                  RD
                                 1,6
                  SET
      &CTR
                                 (&CTR LE &EORCT)
                  WHILE
                                 X '0000 &EOR[&CTR]'
                  COMP
                                 SEXIT
                   TEO
                                 &CTR+1
      &CTR
                  SET
                  ENDW
                  STCH
                                 &BUFADR, X
                  TIXR
                                 $LOOP
                  JLT
                  STX
                                 &RECLTH
      SEXIT
                  MEND
                                                                          (07 Marks)
                                                                          (03 Marks)
   Write a short note on 'Keyword macro parameters'.
                                                                          (12 Marks)
a. List and explain the different design options for a macro processor.
  Write a short note on 'Parser - lexer communication'.
                                                                          (03 Marks)
c. Write a LEX program to count the number of vowels and consonants in a given string.
                                                                          (05 Marks)
a. Explain regular expressions in UNIX with proper examples.
                                                                          (06 Marks)
b. Explain the structure of a YACC program.
                                                                          (06 Marks)
c. Give the LEX and YACC specifications to recognize parenthesized arithmetic expressions.
                                                                          (08 Marks)
```